



XD2000

Bluetooth Configuration Guide

Installation and Configuration

Follow the steps in order to use your terminal with your merchant account and begin accepting credit card payments. If you require assistance with the process or need to find details regarding your accounts, please contact your dealer.

Pre-Installation

Ensure that the terminal is properly connected to an active power source or with a fully charged battery in it. Carefully plug the AC adapter into the terminal (the plug should insert into the power receptacle on the right side of the terminal) and secure it to a live electrical outlet.

Plug Bluetooth adapter into the USB port on the back of the terminal.

Phone support

ExaDigm currently supports the following Bluetooth enabled phones. Please note this list is continuously evolving and being updated. Consult your sales representative for the latest list of supported Bluetooth phone.

Current Phones and carriers:

Cingular Wireless Nokia Model 6230
Cingular Wireless Motorola Model Razr V3
AT&T Wireless Sony Ericsson Model T616
T-Mobile Wireless Nokia Model 6600

USB BlueTooth Modules supported – readily available at most computer stores

Linksys USB Bluetooth adapter model USBBT100
DLINK USB Bluetooth adapter model DBT-120

BlueTooth Configuration

1. Configure the Bluetooth phone:
 - a. Go to the main menu and select the "Connectivity" option
 - b. Select the "Bluetooth" option
 - c. Change the "Bluetooth" option to "On"
 - d. Change the "My phone's visibility" option to "Shown to all"

XD2000 - Bluetooth Configuration Guide

- e. Remember the option under "My phone's name" as this will be used to configure the terminal

*** Note: Configuration of Bluetooth phone may vary for different phones.

2. Configuring the terminal

- a. Admin
- b. Setup
- c. Password : 1234
- d. Communication
- e. Bluetooth
- f. GSM Carrier
- g. Select the "GSM Carrier" according to your wireless service
- h. Select the "Username", "Password" and "APN" appropriately
- i. Press CANCEL twice to return to the Bluetooth MENU
- j. scroll down to the "Phone Name" option and press ENTER
- k. Add a "Phone Name" which is the same as your phone's name from above
- l. Press Power key off and on to reboot the terminal

3. Connecting to the phone

- a. When the terminal tries to connect to the phone, the phone will prompt for a connection pin. This value is defaulted to "12345", but can be changed within the terminal.
- b. The phone will then prompt for accepting the connection from the terminal. Select "Yes" for the same.
- c. Once the terminal shows a signal of some strength then you are ready to use the terminal for transactions. Ethernet Module.

Copyright © 2004 ExaDigm, Inc. All other copyrights and trademarks are property of their respective owners. All Rights Reserved.

Copyright © 2004 ExaDigm, Inc. All rights reserved. No part of this publication may be copied, distributed, stored in a retrieval system, translated into any human or computer language, transmitted in any forms or by any means, without the prior written consent of ExaDigm.